



NOW-Consulting AG

Bettwilerstrasse 14 - 5614 Sarmenstorf - Switzerland

Tel +41 (0)56 667 15 67 - Fax +41 (0)56 667 15 75

RAM und Firmwareanforderung für IPDS-100

What firmware level is required in the hp lj5100, lj8150, lj2300, lj24X0, lj4100, lj4100mfp, lj4200, lj4300, lj4250/4350, lj9000, lj9050, lj9000mfp, lj9055mfp, lj9065mfp, clj3700, clj4600, clj4650, cl

PLEASE NOTE!: This solution, when installed, uses native hp LaserJet device resources such as random access memory (RAM), which may have the effect that certain jobs - that were processed successfully before the installation of the solution - now require more RAM in the device to be processed.

lj2300: The firmware level should be 04.045.0 or higher. PLEASE NOTE: Minimum 48MB RAM is required in the printer. The hp LaserJet 2300l and the LaserJet 2300 comes standard with only 32MB whereas the LaserJet 2300d, 2300n, 2300dn, and 2300dtn all have 48MB.

lj24X0: The firmware level should be 08.007.0 or higher and minimum 64 MB RAM.

lj4100: The firmware level should be 01.019.01 or higher, however, it is recommended to use 01.027.02 or higher as the printer power on time, when the IPDS 100 solution is installed, is up to 5 minutes with the earlier versions. Minimum 48 MB RAM

lj4100mfp: The firmware level should be 03.008.0 or higher and minimum 80 MB RAM

lj4200/lj4200L: The firmware level should be 04.003.2 or higher and minimum 64 MB RAM.

lj4300: The firmware level should be 04.003.2 or higher and minimum 64 MB RAM.

lj4250/lj4350: The firmware level should be 08.007.0 or higher and minimum 64 MB RAM.

lj5100: The firmware level should be MB8.13 or higher and minimum 32 MB RAM.

lj8150: The firmware level should be MB7.109 or higher and minimum 32 MB RAM.

lj9000: The firmware level should be 02.010.2 or higher and minimum 128 MB RAM.

lj9050: The firmware level should be 08.002.0 or higher and minimum 128 MB RAM.

lj9000mfp/lj9000Lmfp: The firmware level should be 03.757.0 or higher and minimum 128 MB RAM .

lj9055mfp: The firmware level should be 07.000.0 or higher and default RAM size.

lj9065mfp: The firmware level should be 07.000.0 or higher and default RAM size.

clj3700: The firmware level should be 06.004.1 or higher and minimum 128 MB RAM.

clj4600: The firmware level should be 03.005.0 or higher and minimum 96 MB RAM.

clj4650: The firmware level should be 07.000.5 or higher and minimum 128 MB RAM.

clj5500: The firmware level should be 04.008.0 or higher and minimum 160 MB RAM.

clj9500: The firmware level should be 05.004.2 or higher and minimum 288 MB RAM.